


# Service Manual

3DO Interactive Multiplayer

FZ-1

**Supplement**



COMPACT  
**disc**  
DIGITAL AUDIO

This is the Service Manual  
for the following area.

...for U.S.A.

Please file and this supplement manual together with the supplement service manual for Model No. FZ-1, Order No. CPD9311017S1.

## Parts Change

### Contents

1. Parts Change .....	1
2. Exploded Views .....	2

#### **⚠ WARNING**

This service information is designed for experienced repair technicians only and is not designed for use by the general public. It does not contain warnings or cautions to advise non-technical individuals of potential dangers in attempting to service a product. Products powered by electricity should be serviced or repaired only by experienced professional technicians. Any attempt to service or repair the product or products dealt with in this service information by anyone else could result in serious injury or death.

**Panasonic**<sup>®</sup>

© 1994 Matsushita Electric Industrial Co., Ltd.  
All rights reserved. Unauthorized copying and  
distribution is a violation of law.

# 1. Parts Change

## CD-ROM DRIVE PARTS

REF. No.	PARTS No.		DESCRIPTION	Q'TY
	ORIGINAL	NEW		
E4	DFWV78H0001	CR-560-BCD-4	Ass'y CD-ROM DRIVE	1
E4-1	LMXA0097	Deleted	Ass'y MECHANISM	1
E4-2	LMXQ0114	Unchanged	Ass'y TRAY	1
E4-3 [1]	LMXA0097	Unchanged	Ass'y HOLDER	1
E4-3 [2]	—	LMXA0116	Ass'y HOLDER	1
E4-4	LMMA0115	Unchanged	BEAM	2
E4-5 [1]	LMEP0253A-2	LMVA0001	CD-ROM DRIVE PCB	1
E4-5 [2]	—	LMEP0306A3	CD-ROM DRIVE PCB	1
E4-6	XSS3+6	Unchanged	SCREW, 3×3mm	4
E4-7	XTN26+8G	Unchanged	SCREW, 2.6×8mm	5
E4-8	—	LMDP0013	LOADING PULLEY	1
E4-9	—	LMDV0004	LOADING BELT	1
E4-10	—	VMXS0336	WASHER	1
E4-11	—	LMMB00771	S.L. SPRING	1
E4-13	—	XQN17+CQ8	SCREW	1
E4-15	—	LMMK0027	FRAME	1
E4-17	—	XYC26+JF8	SCREW	5
E4-21	—	LMXK0153A	Ass'y MECHA. CHASSIS	1
E4-22 NOTE1	LMXY00452	LMXY00473	Ass'y TRAVERSE BASE	1
E4-23	—	LMML00432	SLIDE LEVER 1	1
E4-24	—	LMML0044	SLIDE LEVER 2	1
E4-26	—	LMXG0026	Ass'y LOAD GEAR	1
E4-27	—	LMES0026	Ass'y OPEN SW	1

On the list, [1] and [2] represent versions. They are distinguished by the serial No. Please refer to the following figure and table.



INDEX	DOT	VERSION
A, B, C, D, E	NO	[1]
	YES	[2]
F	NO	[2]
	YES	[2]

**NOTE1:** When you change the TRAVERSE BASE (E4-22):

If the version of the unit is [1], you have to change both E4-3 and E4-5 for version [2] together with E4-22.

## TOP CABINET

REF. No.	PARTS No.		DESCRIPTION	Q'TY
	ORIGINAL	NEW		
K1	DFKM0149ZA-0	DFKM0161YA-0	TOP CABINET	1
K13	DFKE0160ZA-0	Deleted	TOP PANEL	1

## ACCESSORIES

REF. No.	PARTS No.		DESCRIPTION	Q'TY
	ORIGINAL	NEW		
A4	DFJN5001ZAZ	DFJN5001ZBZ	DEMO CD No. 1	1

## MAIN LOGIC PCB

REF. No.	PARTS No.		DESCRIPTION	Q'TY
	ORIGINAL	NEW		
C146, 147 [D]	DCUV1H220JCL	DCUV1H240JCL	CAPACITOR	2
IC180	DA9101KPF-XN	DA858KPF-XN	COLOR ENCODER	1
IC340	DA27C81GW15D	DA5383B0-S	1024K×8bit ROM	1
R704	DBJ6GMJ102VE	DBJ6GMJR00VE	RESISTOR	1

**NOTE:** The mark [D] indicates a kind of the main PCB's. Please refer to the Supplement Service Manual (Order No. CPD9311017S1).

## 2. Exploded Views

